

# CHAT® 150 | CHATAttach™ 150 USB

## Personal/Group Speaker Phones

Speaker phones for individual, small, medium or large group use. The CHAT 150 and CHATAttach 150 USB connect to PCs for rich, full-duplex audio communications and can be used with VoIP softphones, Web collaboration, instant messaging and any other applications requiring two-way audio. A perfect addition to the office or conference room for greatly enhanced collaboration.

**ClearOne**



DELIVERS  
SUPERIOR  
HANDS-FREE  
AUDIO FOR  
PC-BASED  
COLLABORATION  
APPLICATIONS

### APPLICATIONS

- Web Conferencing
  - + IBM Workplace
  - + Microsoft Live Meeting, WebEx
- VoIP Softphones
  - + Avaya, Cisco, Nortel, Mirial
- Internet Telephony
  - + Google Talk, Skype, Vonage
- Instant Messenger
  - + AOL, Microsoft MSN, Yahoo

### ADVANTAGES

- Enable full-duplex speaker phone capabilities on PCs or laptops
  - + Connect the CHAT 150 or the CHATAttach 150 to laptops & PCs via USB for hands-free audio for:
    - > VoIP softphones
    - > Instant Messaging audio chats
    - > Web conferences
- Enjoy rich audio playback
  - + Full bandwidth frequency response provides rich audio playback with media players
- Enjoy crisp, clear audio
  - + Advanced ClearOne HDConference™ audio processing technologies deliver remarkably rich, full audio for natural, effortless conversations:
    - > True full duplex performance allows user to listen and speak at the same time without audio cutting in and out
    - > Distributed Echo Cancellation®
    - > Noise cancellation
    - > Advanced automatic level management
- + Three built-in microphones provide full 360-degree coverage up to 8 feet from device
- + Bridge audio from PC applications with audio on telephone for instant 3-way conference bridge

HDConference™

> **CHAT 150 COMPONENTS**



> **CHATAttach 150 COMPONENTS**

**CHATAttach Packout for the CHAT 150**



**Ready out of the box**


All the components you need to quickly get up and running, including cabling and Quick Start Guide.

**CHATAttach Expansion Cable Packout**




> **ROOM APPLICATIONS**

CHAT 150



CHATAttach 150



**Configuration Software**

Allows users to easily switch between devices; software applies optimized settings to CHAT 150 for each device. Auto-updates from the Web to keep software & CHAT 150 up-to-date with the latest enhancements.

> **SPECIFICATIONS**

**Connections**

USB Connector  
Version 2.0 Compatible  
Type: Mini B Female

Keyed Connector  
Keyed RJ-45 (8 Conductor)

**Controls**

Volume Up  
Volume Down  
Microphone Mute

**Operating System Support**

Windows XP  
Windows Vista  
Windows 7

**Audio**

Speaker  
Bandwidth: 190 Hz - 20 kHz  
Max Output Level: 85 dB SPL @ 1 meter

Microphone  
Bandwidth: 100 Hz - 12 kHz

**Power**

USB-powered  
5 VDC @ 500 mA Maximum

External Power Supply  
100 - 240 VAC Input  
9 VDC @ 560 mA Output

**Environmental**

Operating temperature:  
5 - 40° C (41 - 104° F)

**Mechanical**

CHAT 150 Dimensions (W x D x H):  
7.4" x 7.4" x 1.8"  
(18.8 cm x 18.8 cm x 4.6 cm)

CHAT 150 Weight:  
1.17 lbs (0.53 kg)

**Compliance**

RoHS  
FCC Class A Part 15  
FCC Part 15.19 (A) (3)  
ICES-003  
EU Compliance

**Model Numbers**

**910-156-200**  
**Chat 150 USB**

- Single CHAT 150 and Connecting Cable

**910-156-200-00**  
**CHATAttach 150**

- Two (2) CHAT 150 Devices, Connecting Cables and Power Supply

**910-156-222**  
**CHAT 150 Avaya**

- CHAT 150 and Connecting Cable to Avaya Enterprise Phone

**910-156-220**  
**CHAT 150 Cisco**

- CHAT 150 and Connecting Cable to Cisco Enterprise Phone

**910-156-230**  
**CHAT 150 VC**

- CHAT 150 and Cable to Video Conference System

**Accessory Part Numbers**

**860-156-230L**  
**CHAT 150 VC Accessory Kit**

- Includes Video Conferencing Breakout Box, Power Adapter, International Power Clips, RCA Connection Cable, 25' Link Cable

**860-156-222L**  
**CHAT 150 Avaya Accessory Kit**

- Includes Breakout Box for 2410, 2420, 4610 and 4621 Telephone Handsets, Power Adapter, International Power Clips, RJ-9/RJ-9 Telephone Cable, 25' Link Cable

**860-156-220L**  
**Chat 150 Cisco Accessory Kit**

- Includes Breakout Box for 7940, 7960, and 7970 Telephones, Power Adapter, International Power Clips, RJ-9/RJ-9 Telephone Cable, 25' Link Cable

**910-156-225**  
**CHATAttach Expansion Kit**

- Includes Cables, Power Supply and Quick Start Guide to Update Two (2) CHAT 150 Devices to CHATAttach

> **CLEARONE LOCATIONS**

**Headquarters:**  
**Salt Lake City, UT USA**  
5225 Wiley Post Way  
Suite 500  
Salt Lake City, UT 84116  
**Tel:** 801-975-7200  
**Toll Free:** 800-945-7730  
**Fax:** 801-977-0087  
**e-mail:** sales@clearone.com

**Latin America**  
**Tel:** 801-974-3621  
**e-mail:** global@clearone.com

**EMEA**  
**Tel:** 44 (0) 1189 036 053  
**e-mail:** global@clearone.com

**APAC**  
**Tel:** 801-303-3388  
**e-mail:** global@clearone.com

**Technical Support**  
**APAC**  
**Tel:** 801-283-5936  
**e-mail:** tech.support@clearone.com

\*Other product names may be registered trademarks of their respective owners who do not necessarily endorse ClearOne or ClearOne's products. All rights reserved. Information in this document subject to change without notice.